Ballard Power Systems Europe A/S
Majsmarken 1
9500 Hobro
Denmark

Revision history		
Rev.	**Date.**	**Description**
001	03/02/2023	First Issue
002	17/02/2023	Modified according to comments
003	24/03/2023	Further detailed and expanded
004	18/09/2023	Updated and expanded
005	08/03/2024	Updated according to comments
006	09/04/2024	Exp. to include fan contactors
007	15/10/2024	Updated with changed water separator

Document Title:	**BLPH Project - Electrical Single Line Diagrams**
Document Number:	BPSE-ELE-BPH-DWG-00005
Legacy Number:	K559-2254-CWIWP4202202-C06-001
Revision:	Rev007
Sequence Number:	001
File Name:	K559-2254-CWIWP4202202-C06-001Rev007
Purchaser Job:	K559-2254
Purchase Order:	CWIWP4202202
Code:	C06
Requsition Number:	n/a
Customer:	CrossWind C.V., Rotterdam, The Netherlands

AC Distribution - 40ft Container

Crosswind Scope

Ballard Scope

=HKN70-XB01
3p+N+PE 400Vac
20kW

=BA20+UC50
AC Power Distribution

-XB01
AUX Supply Terminals

-SG01
63 A
Switch Disconnector

-FA01
Uc:277V
Iimp: 25 kA
Surge Arrester

-FC06
2A, B curve
MCB

AUX Customer Supply
Voltage Meas
3ph 400V
-BA01

-BC02
+UC508C03/601.1
+UC508C03/601.1
+UC508C03/601.1
3ph 75A
AUX Customer Supply
Current Trafo

-FC02
50A, C curve
MCCB

-FC12
63A, C Curve
MCCB

-FC10
2A, C-curve
MCCB

Nanogrid Internal
Voltage Meas
3ph 400V
-BA02

-FC01
250A, 3p+N
MCCB

-QA02
55A
Isolation Contactor, 4 pole

-QA01
55A
Isolation Contactor, 4 pole

-FC05
32A, B-curve
MCCB

3p+N 400-480V 50/60Hz

-FC04
63A, B Curve
MCCB

=BA20+DA01

Transformer, dry-type
-TA03
0,46/0,4-0,48
Dyn11 160kVA

=AA01+WZ10
Container Interconnect, Between Containers

BP1 AC Supply from Transformer 250A / 6.3:B

BP2 AC Supply to Container #2 - 32A / 6.3:C

-FC04
160A, 3p+N
MCCB Cooling Skid
+UC30

=LA01+UC20
Control System, Container #1 Inside

-QB01
63A, 3ph+N
Switch Disconnector

3p+N 400-480V 50/60Hz

-FC01A
6A, B-curve
MCCB

-FC01B
6A, B-curve
MCCB

-FC01C
6A, B-curve
MCCB

-FC02
4A, B-curve
MCCB

-FC06
10A, B-curve
MCCB

-FC07
10A, B-curve
MCCB

-FC03A
6A, B-curve
MCCB

-FC03B
6A, B-curve
MCCB

-FC04
10A, C-curve
RCD/MCB

-FC08
20A, B-curve
MCCB

-FC09
20A, B-curve
MCCB

-FC10
20A, B-curve
MCCB

-FC11
10A, B-curve
MCCB

-TB01A
24-28V/40ADC
FCwave PSU
with UPS

-TB01B
24-28V/40ADC
FCwave PSU
with UPS

-TB01C
24-28V/40ADC
FCwave PSU
with UPS

-TB02
24-28V/10ADC
Control PSU
with UPS

-QB02
50A, 24V coil
Contactor

-QB03
50A, 24V coil
Contactor

-QA08
25A
Solidstate
Contactor

-QA09
25A
Solidstate
contactor

-QA10
25A
Solidstate
contactor

-GB01A
UPS Battery
24V, XY Ah

-GB01B
UPS Battery
24V, XY Ah

-GB01C
UPS Battery
24V, XY Ah

-GB02
UPS Battery
24V, XY Ah

1/N/PE

-XD04
1P+N+PE, 1kW
Service

=HE01+UC30
Coolant Skid Cabinet, Container #1 Outside

3p+N 400-480V 50/60Hz

-FC01
6A, B-curve
MCCB

-FC02
2A, B-curve
MCCB

-FC19
25A, B-curve
MCCB

-FC11
6A, B-curve
MCCB

-FC12
6A, B-curve
MCCB

-FC13
6A, B-curve
MCCB

-FC14
6A, B-curve
MCCB

-FC15
6A, B-curve
MCCB

-FC16
6A, B-curve
MCCB

-FC40
13A, B-curve
MCCB

-TB01
24-28V/10ADC
PSU with UPS

-BT02
5°C
Temperature Switch

-GB01
24V Backup Battery
24V, XY Ah

-EA02
0,4W
Cabinet Heater

-TA19
15kW
3x 380-500 VAC
HT Pump Drive

=HE01+UC41
HT + LT VFD Cabinet

-TA11
4.0kW
VFD

-TA12
4.0kW
VFD

-TA13
4.0kW
VFD

-TA14
4.0kW
VFD

-TA15
4.0kW
VFD

-TA16
4.0kW
VFD

-EC40
VFD Cabinet Chiller

=HE01+DA02
HT Cooling System #1, Container #1 Outside

-GP19
15kW
HT1
Coolant Pump

-GQ11
4kW
Ventilation Fan

-GQ12
4kW
Ventilation Fan

-GQ13
4kW
Ventilation Fan

-GQ14
4kW
Ventilation Fan

-GQ15
4kW
Ventilation Fan

-GQ16
4kW
Ventilation Fan

=HE01+UC80
Coolant Skid Cabinet, Container #1 Outside

3p+N 400-480V 50/60Hz

-FC41
20A, B-curve
MCCB

-FC42
20A, B-curve
MCCB

-FC03
2A, B-curve
MCCB

-FC29
25A, B-curve
MCCB

-FC21
6A, B-curve
MCCB

-FC22
6A, B-curve
MCCB

-FC23
6A, B-curve
MCCB

-FC24
6A, B-curve
MCCB

-FC25
6A, B-curve
MCCB

-FC26
6A, B-curve
MCCB

-FC31
6A, B-curve
MCCB

-QA41
25A
Solidstate
contactor

-QA42
25A
Solidstate
contactor

-EA03
Container
Lighting

-TA29
15kW
3x 380-500 VAC
HT Pump Drive

=HE01+UC41
HT + LT VFD Cabinet

-TA21
4.0kW
VFD

-TA22
4.0kW
VFD

-TA23
4.0kW
VFD

-TA24
4.0kW
VFD

-TA25
4.0kW
VFD

-TA26
4.0kW
VFD

-TA31
4.0kW
VFD

-EB01
3x480V, 3x15kW
H2 Heater

9kW
Heating Element

9kW
Heating Element

=HE02+DA02
HT Cooling System #2, Container #1 Outside

-GP29
15kW
HT2
Coolant Pump

-GQ21
4kW
Ventilation Fan

-GQ22
4kW
Ventilation Fan

-GQ23
4kW
Ventilation Fan

-GQ24
4kW
Ventilation Fan

-GQ25
4kW
Ventilation Fan

-GQ26
4kW
Ventilation Fan

=HE03+DA02
LT Coolant System Cooler, Container #1 Outside

-GQ31
4kW
Ventilation Fan

=JA01+DA01
Container Ventilation, Inside Container #1

-EA01
Container
Lighting

-GQ06
4,3 kW
Ventilation Fan

-GQ07
4,3 kW
Ventilation Fan

=JA01+UC07
Container Ventilation, Fan/Heater Assembly

-GQ08
1kW
Ventilation Fan

-GQ09
1kW
Ventilation Fan

-EB01
3x480V, 3x15kW
Container Heater

15kW
Heating Element

15kW
Heating Element

15kW
Heating Element

=HE03+DA01
LT Cooling System, Container #1 Inside

-TA11
4kW
3x380-500VAC
LT Pump Drive

-GP11
4kW
LT Circuit Pump

Reference Item Number	Ballard Part # TBD
EPLAN Project Name	601456B - Shell Baseload Power Hub
EPLAN Revision	03.P17
EPLAN Project Pages	595
~ ++ + & C01	

REVISION INFORMATION	
DESCRIPTION	
DATE	15-Oct-24

THIS DOCUMENT, SUBMITTED IN CONFIDENCE, CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED OR TRANSFERRED TO OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT PRIOR WRITTEN PERMISSION OF BALLARD POWER SYSTEMS INC. OR A RELATED WHOLLY-OWNED SUBSIDIARY OR AFFILIATE.

BALLARD
CONFIDENTIAL

THIS DOCUMENT'S APPROVAL IS MANAGED BY E-SIGNATURE ON FILE IN BALLARD POWER SYSTEMS' PLM SYSTEM

DRAWING	601456B C06 Single Line Diagram
REVISION	03.P17
DRAWING TITLE	Crosswind/Shell Baseload Power Hub, Fuel Cell Container 1MW, no BESS
SHEET TYPE/DESC	Single Line Diagram - 40ft Container AC
ALL SHEETS ARE THE SAME REVISION STATUS	SIZE A1 / LANGUAGE EN / SHEET/TOTAL 4 / 7

FRM510365 3/0B

DC Distribution - 40ft Container

=AA01+WZ10
Container Interconnect, Between Containers

DC1 DC Bus to Container #2 / 6.3:G
DC2 DC Bus to Container #2 / 6.3:G
DC3 DC Bus to Container #2 / 6.3:G
DC4 DC Bus to Container #2 / 6.3:G
DC5 DC Bus to Container #2 / 6.3:G
DC6 DC Bus to Container #2 / 6.3:G

=BA01
Power Conversion Block #1, Container #1 Inside

+UC01
DCDC Cabinet #1, Inside Container #1

-QB01
Switch Disconnector

-FC03
215A

-TA01
DCDC Drive

-TA02
DCDC Drive

-RB01
Converter Inductor

-RB02
Converter Inductor

-FC01
315A

-FC02
315A

+UC02
DCDC Cabinet #2, Inside Container #1

-QB01
Switch Disconnector

-FC03
215A

-TA03
DCDC Drive

-TA04
DCDC Drive

-RB03
Converter Inductor

-RB04
Converter Inductor

-FC01
315A

-FC02
315A

+UC03
DCDC Cabinet #3, Inside Container #1

-QB01
Switch Disconnector

-FC03
215A

-TA05
DCDC Drive

-TA06
DCDC Drive

-RB05
Converter Inductor

-RB06
Converter Inductor

-FC01
315A

-FC02
315A

=BA02
Power Conversion Block #2, Container #1 Inside

+UC04
DCDC Cabinet #4, Inside Container #1

-QB01
Switch Disconnector

-FC03
215A

-TA07
DCDC Drive

-TA08
DCDC Drive

-RB07
Converter Inductor

-RB08
Converter Inductor

-FC01
315A

-FC02
315A

+UC05
DCDC Cabinet #5, Inside Container #1

-QB01
Switch Disconnector

-FC03
215A

-TA09
DCDC Drive

-TA10
DCDC Drive

-RB09
Converter Inductor

-RB10
Converter Inductor

-FC01
315A

-FC02
315A

+UC06
DCDC Cabinet #6, Inside Container #1

-QB01
Switch Disconnector

-FC03
215A

-TA11
DCDC Drive

-TA12
DCDC Drive

-RB11
Converter Inductor

-RB12
Converter Inductor

-FC01
315A

-FC02
315A

=RE01
Fuel Cell Block 1

+GB01
Fuel Cell Module 1

-GB01
720-350V, 0-300A
Fuel Cell Stacks

-GB02
720-350V, 0-300A
Fuel Cell Stacks

+GB02
Fuel Cell Module 2

-GB01
720-350V, 0-300A
Fuel Cell Stacks

-GB02
720-350V, 0-300A
Fuel Cell Stacks

+GB03
Fuel Cell Module 3

-GB01
720-350V, 0-300A
Fuel Cell Stacks

-GB02
720-350V, 0-300A
Fuel Cell Stacks

=RE02
Fuel Cell Block 2

+GB04
Fuel Cell Module 4

-GB01
720-350V, 0-300A
Fuel Cell Stacks

-GB02
720-350V, 0-300A
Fuel Cell Stacks

+GB05
Fuel Cell Module 5

-GB01
720-350V, 0-300A
Fuel Cell Stacks

-GB02
720-350V, 0-300A
Fuel Cell Stacks

+GB06
Fuel Cell Module 6

-GB01
720-350V, 0-300A
Fuel Cell Stacks

-GB02
720-350V, 0-300A
Fuel Cell Stacks

Reference Item Number	Ballard Part # TBD
EPLAN Project Name	6014568 - Shell Baseload Power Hub
EPLAN Revision	03.P17
EPLAN Project Pages	595
=	++ | + | & C01

REVISION INFORMATION	
DESCRIPTION	
DATE	15-Oct-24

THIS DOCUMENT, SUBMITTED IN CONFIDENCE, CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED OR TRANSFERRED TO OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT PRIOR WRITTEN PERMISSION OF BALLARD POWER SYSTEMS INC. OR A RELATED WHOLLY-OWNED SUBSIDIARY OR AFFILIATE.

BALLARD
CONFIDENTIAL

THIS DOCUMENT'S APPROVAL IS MANAGED BY E-SIGNATURE ON FILE IN BALLARD POWER SYSTEMS PLM SYSTEM

DRAWING	6014568 C06 Single Line Diagram
REVISION	03.P17
DRAWING TITLE	Crosswind/Shell Baseload Power Hub, Fuel Cell Container 1MW, no BESS
SHEET TYPE/DESC	Single Line Diagram - 40ft Container DC
ALL SHEETS ARE THE SAME REVISION STATUS	SIZE A1 | LANGUAGE EN | SHEET/TOTAL 5 / 7

FRMS103653/0B

AC/DC Distribution - 10ft Container

Crosswind Scope

Ballard Scope

=AA01+WZ10
Container Interconnect, Between Containers

4.15:B / 3ph AC Supply to Container #1 - 250A BP1

4.15:B / 3ph+N AC Supply from Container #1 - 32A BP2

3ph 400-480V, 50-60Hz

=LA01+UC31
Control System, Container #2 Inside

-QB01
32A, 3p+N
Switch Disconnector

3ph+N 400-480V, 50-60Hz

-FC01
4A, B-curve
MCCB

-TB33
24-28V/10ADC
PSU with UPS

-GB01
UPS Battery
24V, XY Ah

-FC03
13A, B-curve
MCCB

-QA03
4...32 V DC/48...600 V AC
Solidstate contactor
Container Heating

-FC04
10A, B-curve
MCCB

-FC07
4A, B-curve
MCCB

-EA07
Room Lighting

-FC08
10A, C-curve
RCB/MCB

-XD08
1kW
Service Outlet

=JA01+DA03
Container Ventilation System, Inside Container #2

-EB03
10kW
Container Heating

-GQ10
5,7kW
Ventilation Fan

=BA30+DA03
Power Conversion Output, Inside Container #2

=HKN70-XB02
3ph 6,6 kV

=HKN70-FC01
MV Circuit Breaker

-TA30
1250kVA
400/6600V Transformer
Dry-type

-FC31
250A
250A Breaker

-FC30
2000A
2000A Breaker

-FC40
2.5..4A
Circuit Breaker
for Primary Transformer Protection

-RB30
500V, 840A
0,084mH, 203uF
LC Filter

-RB31
500V, 840A
0,084mH, 203uF
LC Filter

-TA40
0,4/0,4 kV, 2kVA
Isolation Transformer

-TB30
1640 A, 3x 400-500 VAC
Active Front End

-QA40
Precharge Contactor

-TB40
60A
Rectifier, 3ph doide bridge

-RA40
4 pcs 3,3Ω, 1000W
Resistor

-FC29
800A
Fuse

-FC32
800A
Fuse

-FC41
20A

DC Busbar System

-XD01:1 -XD01:7

5.15:B / DC Bus from Fuel Cells DC1

5.15:B / DC Bus from Fuel Cells DC2

5.15:B / DC Bus from Fuel Cells DC3

6x (2x120 mm2)

5.15:B / DC Bus from Fuel Cells DC4

5.15:B / DC Bus from Fuel Cells DC5

5.15:B / DC Bus from Fuel Cells DC6

Reference Item Number	Ballard Part # TBD
EPLAN Project Name	6014568 - Shell Baseload Power Hub
EPLAN Revision	03.P17
EPLAN Project Pages	595
=	++ | + | & C01

FRM5103653/0B

REVISION INFORMATION	
DESCRIPTION	
DATE	15-Oct-24

THIS DOCUMENT, SUBMITTED IN CONFIDENCE, CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED OR TRANSFERRED TO OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT PRIOR WRITTEN PERMISSION OF BALLARD POWER SYSTEMS INC. OR A RELATED WHOLLY-OWNED SUBSIDIARY OR AFFILIATE.

BALLARD
CONFIDENTIAL

THIS DOCUMENT'S APPROVAL IS MANAGED BY E-SIGNATURE ON FILE IN BALLARD POWER SYSTEMS' PLM SYSTEM

DRAWING	6014568 C06 Single Line Diagram
REVISION	03.P17
DRAWING TITLE	Crosswind/Shell Baseload Power Hub, Fuel Cell Container 1MW, no BESS
SHEET TYPE/DESC	Single Line Diagram - 10ft Container
ALL SHEETS ARE THE SAME REVISION STATUS	SIZE A1 | LANGUAGE EN | SHEET/TOTAL 6 / 7